

Kortfattad instruktion

Du installerar programvaran som medföljer på din dator.

Sen kopplar du WiFi,n till din dator och startar programmet, det kommer då först hitta din WiFi sen kommer den visa vilka trådlösa nät som finns tillgängliga.

Välj ditt trådlösa nät och lägg in din nyckel sen är du klar.

Sen kan du flytta din WiFi till vilka trådbundna enhet som helst.

WiFi tar ström via en USB port om du har en DM800.

Om du har en DM500 kan du koppla matningen först till WiFi sen vidare till boxen.

Om du ska använda den till någon annan nätverksenhet som inte har USB måste du ha en strömadapter, som inte medföljer, DC5V-15V

Detaljerad instruktion

Installera programmet som är på medföljande skiva, på en dator, helst på en med Win7.

Om ni får felmeddelande "NIC not found" prova att ladda ner en nyare version av programmet WAP11G från min hemsida www.keltir.se

Om ni har trådlöst nätverkskort i datorn måste det inaktiveras.

Ev. stäng av antivirusprogrammet.

Om inget av detta hjälper prova med en annan dator.

När programmet är installerat

Anslut WiFi-bridgen, både USB- och nätverkskabeln i din dator.

Starta programmet dubbelklicka på ikonen **VAP11G**

Markera adressen, tryck på Next

VONETS

WIFI-Bridge Setup S.O.11

1 Select WIFI-Bridge

List of all WIFI-Bridge on Network Refresh List

Select your WIFI-Bridge from the list and click Next.

Name	Mac Address
00-17-13-10-7b-f3	00-17-13-10-7b-f3

Click the Refresh list button to find WIFI-Bridges that have recently been added to the network.

Back Next Exit

802.11B/802.11G WIFI-Bridge Setup Wizard Model: VAP11G

Välj och markera ditt trådlösa nätverk, tryck på Next (jag har dlink, grannen har netgear)



Choose a Wireless Network

2 Select a Wireless Network to connect to. If the wireless network is not found, please click [Refresh list](#), or enter the SSID of the network manually. Then, click [Next](#).

SSID	Mac Address	Chan...	Signal	Security	Speed
dlink	00265a5775e4	6	10%	WPA-P...	54Mbps
NETGEAR	30469a570e2c	6	10%	WPA2-...	54Mbps


[Refresh List](#)

SSID You can manually enter the SSID of the wireless network.

There are 2 wireless networks. [Back](#) [Next](#) [Exit](#)

802.11B/802.11G WIFI-Bridge **Setup Wizard** Model: **VAP11G**

Skriv in er nyckel för ert trådlösa nätverk, tryck Next



Security Settings

3 If you would like to use Wi-Fi Protected Access(WPA), enter the required information below.

Security WPA-PSK Please choose disabled, WEP (64-bit), WEP (128-bit), WPA, or WPA2.

Encryption TKIP TKIP is automatically selected as the encryption for WPA.

Passphrase 1234567890 Enter the passphrase that will be used to generate the WPA key. The passphrase is case-sensitive and should be between 8 and 63 characters in length.

[Back](#) [Next](#) [Exit](#)

802.11B/802.11G WIFI-Bridge **Setup Wizard** Model: **VAP11G**

Bekräfta med Next två gånger.

VONETS

Confirmation

3 Review the new settings before you save them.
Confirm NEW Settings

Old Settings	New Settings
Channel: Auto	Channel: Auto
Network Type: Infrastructure	Network Type: Infrastructure
SSID: dlink	SSID: dlink
Security: WPA-PSK	Security: WPA-PSK

Back Next Exit

802.11B/802.11G WIFI-Bridge Setup Wizard Model: VAP11G

Klart

VONETS

Congratulations

Ige has
ured!

✓ Configurations have been saved successfully!

Visit Vonets Back Next Exit

802.11B/802.11G WIFI-Bridge Setup Wizard Model: VAP11G

Nu kan du prova att komma ut på Internet.

Funkar det så kan du flytta WiFi-Bridgen till Dreamboxen eller någon annan trådbunden nätverksenhet.